

<b>AZ Controller</b>		
<b>Preset for X-Touch One (custom CUBASE layout)</b>		
X-Touch One key name	Function	SHIFT-function (hold Scrub to SHIFT)
<b>CHANNEL</b>		
Beats / Time	Toggle time display (MBT / SMPTE)	Show/Hide Dock
Master Level	Master select	-
Ch. Select	Channel select	-
Ch. Mute	Channel Mute	Unmute All Tracks/Busses
Ch. Solo	Channel Solo	Unsolo All Tracks/Busses
Ch. Rec	Channel Arm / Disarm	Disarm All Tracks
<b>FUNCTION section</b>		
F1	Insert Audio Track	Insert Midi Track
F2	Insert From Template (Can use Arrows and Shift-Zoom (enter) to select)	Insert Track Folder
F3	Toggle Tracks/Busses (Monitored on device)	Insert Stereo Bus
F4	Toggle Input Echo (Monitored)	Select All / Export
Automation Read	Automation Read (Monitored)	Toggle all read Automation
Automation Write	Automation Arm / Disarm (Monitored)	Disarm all Write automation
<b>TRANSPORT</b>		
Undo	Undo	Undo History
Redo	Redo	Split Clips at Now
Cycle	Toggle Loop	Set Loop points to selection
Punch In	Toogle Rewind to Now-marker on Stop	Set Punch points to selection
Previous Marker	Previous Marker	Show Console
Set Marker	Insert new marker	Select all between previous marker and next (for cycle / punchin)
Next Marker	Next Marker	Show PRV
<<	Rewind	Go to start (RTZ)
>>	Fast Forward	Go to end
Stop	Stop	Reset MIDI & Audio
Play	Pay	Run/Stop Audio Engine
Record	Record	Save
<b>OTHER CONTROLS</b>		
Fader	Volume	-
Fader1 (touch)	Channel select	-
Pan < - >	Pan	-
Push	Centre Pan	-
Fader Bank <	Previous Fader Bank	Go to First group of 8
Fader Bank >	Next Fader Bank	Go to Last Group of 8
Channel <	Previous Channel	-
Channel >	Next Channel	-
Left	Left / Horizontal Zoom	Shift-Tab
Right	Right / Horizontal Zoom	Tab
Up	Up / Vertical Zoom	-
Down	Down / Vertical Zoom	-
Zoom	Toggle Zoom Fits all tracks to screen on exit	Enter
Jog wheel	Scroll Beat (MBT mode) or Second (SMPTE-mode)	Scroll Tick (MBT mode) or Frame (SMPTE-mode)
Scrub	Shift	-